


# MultiTransmitter Fibra

Module to integrate third-party wired detectors and devices into an Ajax security system.



The device is compatible only with hubs supporting Fibra protocol. Find the detailed information via QR code or at the link:



<https://ajax.systems/support/devices/multitransmitter-fibra/>



2  
GRADE  
EN 50131


PD 6662  
2017



MultiTransmitter Fibra is a wired device of the Fibra product line. Only accredited partners of Ajax Systems can purchase, install and administer Fibra devices.



18 inputs for third-party wired devices



Up to 400 m of cable length between devices and MultiTransmitter Fibra



One of 9 types of events to be chosen for each connected device

## The second life of an old wired alarm

MultiTransmitter Fibra allows building the modern complex security based on existing third-party wired equipment already installed at a facility. With this integration module, the owners of an old alarm system receive the in-app security modes control, informative notifications, and automation scenarios from Ajax. An installer can configure the system or connected devices in the PRO app remotely, even without visiting a facility.

# Maximum compatibility

MultiTransmitter Fibra does not limit users in their selection of wired devices to connect. The integration module supports NC, NO, EOL, 2EOL, and 3EOL connection types. EOL resistance is set automatically in the Ajax PRO app.

The device supports EOLs with resistance from 1 kΩ to 15 kΩ each with total resistance of 30 kΩ. EOLs with different resistance can be used in one device in order to increase the protection against sabotage.

Recommended EOL ratio:  $R1 = R$  ,  $R2 = 2 \cdot R$  ,  $R3 = 3 \cdot R$  .

MultiTransmitter Fibra has four 12 V= power outputs for third-party wired devices: one for a fire detector and three for other devices.




**Fibra** is the **protocol** ensuring fast and secure two-way communication between hub and MultiTransmitter Fibra. Using a bus connection method, Fibra delivers instant **data-rich alarms**: security companies and users know which device connected to MultiTransmitter Fibra was triggered, when and where it happened.

Fibra features **encryption** and **authentication** to prevent spoofing, and **polling** to display device states in real time. Supporting **up to 2,000 m of wired connectivity**, Fibra is ready to protect any facilities and deliver the best user experience for both system owners and installers.

## Technical specifications

Compliance with standards	<b>EN 50131 (Grade 2)</b> <b>PD 6662:2017</b>	Connected devices	<b>Number of zones</b> <b>18</b> One wired device per zone
			<b>Connection types</b> NC, NO, EOL, 2EOL, 3EOL

<p>Communication with control panel</p>	<p> <b>Fibra communication technology</b></p> <p><b>Communication range</b> up to 2,000 m with U/UTP cat.5 cable, 4×2×0,51</p> <p><b>Polling interval</b> 12–300 s Adjusted by PRO or user with admin rights</p> <p><b>Protection against spoofing</b> MultiTransmitter Fibra authentication</p>	<p>Connected devices</p>	<p><b>EOL resistance</b> from 1 kΩ to 15 kΩ for each resistor, up to 30 kΩ of total resistance Set automatically in PRO apps</p> <p><b>Operating modes</b> pulse, bistable Set by PRO or user with admin rights</p> <p><b>Types of events</b> intrusion, fire, medical help, panic button, gas alarm, tamper alarm, malfunction, leakage, custom Set by PRO or user with admin rights</p> <p><b>Cable length between devices and MultiTransmitter Fibra</b> up to 400 m When using a signal cable with a 0.22 mm<sup>2</sup> copper-clad aluminium conductor</p> <p><b>Power supply for connected devices</b> 4 power outputs: 10.5–15 V<sub>DC</sub>, up to 1 A in total One power output for a fire detector, and three outputs for other devices</p>
<p>Compatibility</p>	<p><b>Hubs</b> Hub Hybrid (2G) Hub Hybrid (4G)</p> <p><b>Range extenders</b> no</p>	<p>Power supply</p>	<p><b>Main power supply</b> 100–240 V, 50/60 Hz</p> <p><b>Backup power supply</b> 12 V<sub>DC</sub> lead acid battery with up to 7 A·h capacity and a full charge cycle of up to 30 h Backup battery not included</p>

<p>Installation</p> <p><b>Operating temperature range</b> from -10°C to +40°C</p> <p><b>Operating humidity</b> up to 75%</p> <p><b>Protection class</b> IP40</p>	<p>Casing</p> <p><b>Colour</b> white, black</p> <p><b>Dimensions</b> 196 × 238 × 100 mm</p> <p><b>Weight</b> TBC</p> <p><b>Tamper alarm</b> Two tampers to detect the lid opening and alert of detachment a module from the wall</p>
<p>Complete set</p> <p>MultiTransmitter Fibra Casing Power cable Screw terminal block Adapter* 12 V<math>\Rightarrow</math> battery connection cable Installation kit Quick Start Guide</p>	

\* Only for INCERT compliance