

Datasheet

Instruction

The DNAKE C112 enables you to make the video call with villa entrance door, and open the door remotely from indoor monitor or mobile APP. It also makes an easy integration with SIP devices.

DNAKE C112 (Surface Mounting)



Key Features

- Compact Design
- 2MP, 1080P HD Camera, digital WDR
- H.265 Video Codec
- Optional IC card reader, WIFI and Bluetooth
- Tamper Alarm

Physical

- System: Linux
- Front Panel: Plastic
- Power Supply: PoE (802.3af) or DC 12V/2A
- Camera: 2MP, CMOS, WDR
-
- Wiegand Port: Support
- Wi-Fi: IEEE802.11 b/g/n, @2.4GHz (Optional)
- Bluetooth: Bluetooth (Optional)
- TF Card Slot: 1
- Ethernet Port: 1 x RJ45, 10/100 Mbps adaptive
- Door Entry: IC (13.56MHz) card (Optional)
- Reset Button: 1
- RS485 Port: 1
- Relay Out: 1
- Input: 2
P65
- Installation: Surface Mounting
- Surface Mounting DIM: 130 x 50 x 28 mm
- Working Temperature: -40°C to +55°C
- Storage Temperature: -40°C to +70°C
- Working Humidity: 10% to 90% (non-condensing)



Datasheet

Audio

- Audio Codec: G.711
- Echo Cancellation
- DTMF: RFC2833
- Microphone: Built-in microphone
- Speaker: Built-in speaker

Networking

- Protocol: SIP, UDP, TCP, RTP, RTSP, NTP, DNS, HTTP, DHCP, IPV4, ARP, ICMP

Video

- Video Codec: H.264, H.265
- Video Resolution: 1920 x 1080
- Viewing Angle: 110° (H) / 60° (V) / 125° (D)
- Max. Image Transfer Rate: 1080p – 25fps
- Light Compensation: LED white light

