

DS-PT1-WE Wireless Tag Reader

DS-PT1-WE wireless tag reader can connect to wireless security control panel for arming/disarming. It can also notice alarm by indicator and buzzer.







Available Model

• DS-PT1-WE



Key Feature

- 868MHz two-way wireless communication
- AES-128 encryption
- LED display, show the differernt feedbacks with easy understanding
- Operation: Stay arm/away arm/disarm by areas
- Arming process with fault confirm, more secure
- Patrol tag check in
- Front and rear panel tamper-proof



Specification

Model		DS-PT1-WE Wireless Tag Reader
RF	Frequency	868 MHz
	RF method	Two way communication
	RF encryption	AES-128
	Modulation	2GFSK
	RF distance	1200m(open area)
Interface & component	TAMPER switch	1
	Power switch	Power on/off
	Indicator	5, area(blue), fault(orange), arm(blue), disarm(green), alarm(red),
		signal(red/green)
	Buzzer	Prompt for tag operation, entry/exit delay and tamper/alarm
Electrical & battery	Power Consumption	Quiescent current: 110 uA
		Max current: 292mA
		Voltage: 1.5 VDC
	Battery type	Three AA batteries
	Battery life span	2 years (swipe tag 10 times per day)
Others	Operation humidity	10% to 90% (no condensing)
	Operation temperature	-10°C to +55°C (-4°F to +122°F)
	Dimension (W × H × D)	75*124*21 mm
	Weight	176g (with battery)
	Color	white
	Installation	Wall mounting



Distributed by

HIKVISION'

Headquarters

No.555 (kanmo Road, Binjiang District, Hangzhou 310051, China T+86-571-8807-5998 overseasbusiness@hikvision.com

Hikvision USA T+1-909-895-0400 sates.usa@hikvision.com

Hillorision Australia T+61-2-8599-4233 salesau@hik/ision.com

Hikvision India T 491-22-28469900 sales@pramahikvision.com

Hikvision Canada T +1-866-200-6690 sales.caneda@hikvision.com

Hikvision Thailand T +682-275-9949 sales.thailand@hikvision.com Hikvision Europe T+31-23-5542770 sales.eu@hikvision.com

Hillovision Italy T+39-0438-6902 Info.it@hillovision.com

Hikvision Brazil T +55 11 3318-0050 Lutam.nupport@fisiors.com

Hikvision Turkey T+00 (210)521 7070- 7079 sales.bi@hikvision.com

Hikvision Malaysia T+601-7652-2413 sates.my@hikvision.com Hillovision UK & Ireland T+01628-902140 sales.uk@nkytsion.com

Hillovision South Africa Tet. +27 [10] 0351172 sate.africa@billovision.com

Hillorision France T +330(1-85-330-450 info.fv@hillorision.com

Hillovision Kazakhstan T +7-727-9730667 nikis.ponfilov@hikvision.ru

Hillovision Vietnam T +84-974270888 sales.vt@hillovision.com Hikvision UAE 7 +971-4-4432090 salesme@inlkvision.com

Hikvision Singapore T +65-5589-4718 sg@hikvision.com

Hikvision Spain T +34-91-737-16-55. info.es@hikvision.com

Hikvision Tashkent T +89-87-1238-8438 uzb@hikvision.ru

Hikvision Hong Kong T+852-2151-1781 Info.hk@hikvision.com Hikvision Russis T+7-465-889-67-99 saleru@hikvision.com

Hikvision Korea T +82-(0)31-731-8817 sales korea@hikvision.com

Hikvision Poland T +48-22-468-01-50 info_pi@nikvision.com

Hkvision indonesia T +62-21-2933759 Sales indonesia@Wkvision.com

Hikvision Colombia sales.colombia@hikvision.com